

## Specification:

- 1. JK801: uniformed key for all switches
- 2. JK802: unique key for each switch
- 3. 2 keys for each switch

## **Technical Requirement:**

JK801 / JK802

- 1. Can be pulled out easily at OFF position Pulling force  $\leq 2 \text{ kgf } (19.6 \text{ N})$
- 2. Can be turned freely between OFF and ON positions
- - a) Pin 1 (BAT): 4.0 amperes max.
  - b) Pin 2: 2.5 amperes max.
  - c) Pin 3: 1.5 amperes max.d) Total power rate: ≤ 180 watts
- 4. No flaw at surface
- 5. Life span:  $\geq$  50,000 times @ full load
- 6. Compliance with standard

## Working Principle:

		•	
Pin Position	1	2	3
OFF			
ON	0	-0-	-0

Q	C/	Γ50	04-199	99						
						-			www.noco-evco.com	
	标记	处数 计	更改文件	名 签	宇日期	图样标记	重量	比例	Key Operated Switch	
							-	1:1	JK801 / JK802	
				日期		共 张	第	张	310001 / 310002	